

GW系列熔炼炉主要技术参数
Main technical parameter of Gw series melting furnace

感应炉额定容量 Rated capacity t	配用的变频电源			
	额定功率推荐范围 Power range kW	频率推荐范围 Frequency range HZ	进线输入电压或者电压范围 Incoming voltage range V	熔化率范围 Melting t/h
0.1~0.15	100	1000~2500	380~660	0.15~0.25
0.25~0.5	200-500			0.32~0.84
0.75~1	600-800			1.05~1.40
1.5	750-1200	500~1000	575~1250	1.35~2.20
2	1000-1600			1.80~2.90
3~4	1500-3000	500	575~1250	2.75~5.50
5	2000-3500			3.64~6.45
8~10	2500-6000	200~500	575~1400	5.45~11.10
12~15	4000-8000	150~500	1250~1500	9.10~16.80
20~30	6000-12000	200~300	1400~1600	14.90~27.50
40~60	12000~20000	150~250	1500~1600	21.30~53.10
70~100	20000~25000	100~150	1600~1850	37.20~53.10